
Guía del usuario

- Encendido
- Principio de funcionamiento ON/OFF: Los aparatos conectados funcionan/se detienen a través del encendido/apagado del cable vivo.




Nota: El interruptor ZigBee debe estar alimentado por cables N y L

Como conectar:

1. Enchufe el dispositivo
2. Encuentre un punto de acceso wifi abierto con la palabra Tasmota en el nombre
3. Conéctese a él y vaya a la dirección 192.168.4.1 en el navegador
4. Ingrese su nombre de red wifi y contraseña
5. Después de confirmar los datos de la red, la regleta le mostrará la dirección IP desde la que estará disponible, cópiela, por si acaso.
6. Lo redirigirá automáticamente a esta dirección después de que se llenen y guarden los datos de su red.
7. La regleta está lista para usar. La plantilla y las reglas ya están activadas, pero en caso de que las necesite más adelante, puede encontrarlas a continuación.

Parámetros de la plantilla:

{"NOMBRE":"Módulo de cortina WiFi inteligente L12T","GPIO":[1,161,1,160,225,224,1,1,544,1,32,1,1,1],"BANDERA":0,"BASE":18}



El uso de esta plantilla convierte la unidad en un simple interruptor de 2 elementos (p. ej., L13 [2 elementos]).

Para operar la unidad como un interruptor de persiana enrollable, se deben emitir los siguientes comandos:

- habilitar SetOption80 1
- activar ShutterRelay1 1
- Interlock 1,2
- Interlock ON
- set the switches to follow and inverse `SwitchMode1 4` and `SwitchMode2 4`. Check SwitchModes documentation for details.
- Then the device should be calibrated for the distance of your curtains, have a look at Blinds and Shutters configuration page.

if there is power button:

Hold the power button 40+ seconds, untill light blinks and device restarts

if there is no power button:

Plug the device in and out 6 times and leave plugged in on the 7th - LED should start to blink, that means socket is ready to be connected again

if have access to the web interface:

type **reset 1** in console and press enter

Smart Home Intergations

Tasmota is Incredibly expandable and flexible and can be integrated with:

Alexa, AWS IoT, Domoticz, Home Assistant, Homebridge, HomeSeer, IP Symcon, KNX, NodeRed, nymea, OctoPrint, openHAB, Otto, IOBroker, Mozilla WebThings Adapter, SmartThings, Tasmohab, Homematic ip, etc.

para obtener más información, consulte aquí:
https://tasmota.github.io/docs/Integrations/